

Worldwide distributor: Audioscope 2k S.r.l.

Q-Remote.

- 1RU standard unit.
- Controls via LAN one Multiviewer unit.



Q-Remote front panel controls:

- Power switch: It powers ON/OFF the unit.
- Pw1 LED: It is normally green to indicate that the main internal +24V power supply is present.
- Pw2 LED: It is normally green to indicate that the backup internal +24V DC power supply is present.
- The "Fail" red LED is ON if failure of one or more ventilation fans of the unit have been detected.
- USB for keyboard to insert UMD's and recall presets.
- 6 x Keys to navigate the on screen menu,
- 10 x Keys to remotely recall video presets.

Q-Remote Rear Panel.



- LAN connector to connect to a PC or Network.
- Socket for the RS422 connection to the multiviewer.